

MP210U MP310U MP610U MP1010U MIXER AMPLIFIER



Features

- Integrates MP3 player, FM tuner, zoner (6 zones), preamplifier and power amplifier.
- Infrared remote control to control MP3/TUNER, which includes modes switches, program selection, volume adjustment, repeat mode, EQ mode and USB/SD switches.
- LED display indicates volume, playing status, program number, etc.
- 4 MIC inputs, 3 AUX inputs, and 1 AUX output.
- 4-16 Ω rated output.
- 6-zone selector, individual volume control and output level indication for each zone output.
- Mute function for priority input.
- Treble and Bass control
- Chime with priority output
- 5-unit LED indicates monitoring volume output in each zone.
- Output short circuit protection and caution.

Specifications

Model	MP210U	MP310U	MP610U	MP1010U
Rated Output	60W	120W	250W	350W
Output regulation	≤3dB (from off-load to full load)			
Input sensitivity	Microphone : ≤3mV (unbalanced)			
	Line: ≤300mV (unbalanced)			
Frequency response	80Hz-16KHz (±3dB)			
Distortion	≤1% (1KHz, normal operating status)			
S/N Ratio	Line: ≥74dB			
Tone	Bass: ±10dB (at 100Hz)			
	Treble: ±10dB (at 10kHz)			
Protection	DC voltage; overload; short-circuit.			
Mute	Input signals from MIC 1 override other input signals			
Power supply	AC 220-240V/50-60Hz			
Power Consumption	120W	250W	500W	650W
Outer Packing Size(mm)	(L×W×H)555×455×185			
Unit Size (mm)	(L×W×H)484×355×88			
Gross Weight	11.7kg	13.5kg	16kg	17kg
Net Weight	9.7kg	11.5kg	14kg	15kg